

Eaton Nova AVR UPS



Eaton® Nova AVR® UPSs provide the user with cost-effective, rugged protection against electrical interference and power outages

- Line-interactive technology (automatic voltage regulation via buck and boost)
- Wide tolerance to fluctuations in the power supply (89–151V)

Data line filtering for total protection

- The Nova AVR is equipped with protection for data lines to prevent surges and the destruction of sensitive electronic components

Easy to use and maintain—very simply, the Nova AVR uses:

- Three indicator lamps to display the principal states (On/Off, Replace Batteries, Fault), supplemented by audible alarms
- The batteries are easy to replace
- The cold start function can turn the Nova AVR into a mobile power source for IT equipment

Unique network connectivity

- The Nova AVR can be remotely monitored over the network from a simple Web browser or an enterprise SNMP platform at no extra cost

600 VA UPS



1100 VA UPS



Powering Business Worldwide

NOVA AVR, Model Selection Guide

Catalog Number	Style Number	Rating (VA/Watts)	Input Connection	Output Receptacles	Dimensions (H x W x D, inches)	Weight (lb)
NVAL600T-USB	81601	600/360	5-15P	(3)5-15R	5.6 x 4.9 x 13.8	15.0
NVAL1100T-USB	81111	1100/660	5-15P	(4)5-15R	7.4 x 6.7 x 14.8	26.9

Battery Backup Times (in minutes*)

	Load (VA/Watts)			
	150/90	300/180	450/270	600/360
NOVA AVR 600	25	11	5	3

The Nova AVR 600 powers a typical PC for approximately 15 minutes.

	Load (VA/Watts)			
	275/165	550/330	825/495	1100/660
NOVA AVR 1100	24	10	4	1

The Nova AVR 1100 powers a typical PC for approximately 30 minutes, two PCs for 15 minutes and three PCs for 8 minutes.

* Backup times are approximate and may vary with equipment, configuration, battery age, temperature, etc.

Technical specifications¹

TOPOLOGY Line-interactive with +18% boost and -15% buck

INPUT/OUTPUT

Input voltage	89–151V
Output voltage	120V
Frequency	50/60 Hz auto-detection
Surge protection	Total energy dissipation: 127 Joules
Protection	User-resettable circuit breaker
Data line protection	Yes

BATTERIES

Battery recharging	Continuous battery recharging, even if the On/Off button is set to Off
Battery monitoring	Battery replacement indicator (red LED)
Replaceable batteries	Access via the front panel
Startup without mains power (cold start)	Can be used as a mobile power source
User interface	(1) illuminated On/Off button, (1) Fault and Overload LED, (1) battery Fault LED and audible alarms

TECHNICAL STANDARDS

Safety and EMC UL, cUL, EN 50 091, IEC 62 040, CE logo

NETWORK INTERFACE

Communication port	USB
Communication cable	Included
Web/SNMP management	With Network Management Proxy (free download from Eaton Web site)
Power management software	Available for Windows, Mac OS, Linux and more

WARRANTY Two years



vmware® | technology alliance
PARTNER

UNITED STATES
8609 Six Forks Road
Raleigh, NC 27615 U.S.A.
Toll Free: 1.800.356.5794

www.eaton.com/powerquality

CANADA
Ontario: 416.798.0112

LATIN AMERICA
Argentina: 54.11.4343.6323
Brazil: 55.11.3616.8500
México: 52.55.5488.5252

EUROPE/MIDDLE EAST/AFRICA
Denmark: 45.3686.7910
Finland: 358.94.52.661
France: 33.1.6012.7400
Germany: 49.0.7841.604.0
Italy: 39.02.66.04.05.40
Norway: 47.23.03.65.50
Portugal: 55.11.3616.8500
Sweden: 46.8.598.940.00
United Kingdom: 44.1753.608.700

ASIA PACIFIC
Australia/NZ: 61.2.9693.9366
China: 86.21.6361.5599
HK/Korea/Taiwan: 852.2745.6682
India: 91.11.2649.9414 to 18
Singapore/SEA: 65.6829.8888

Eaton, Nova AVR and Pulsar are trade names, trademarks and/or service marks of Eaton Corporation or its subsidiaries and affiliates.



Powering Business Worldwide

©2009 Eaton Corporation
All Rights Reserved
Printed in USA
NOVA01FXA
March 2009